

Anlage 3 zum Anhang

**Übersicht der BOS-Frequenzen im Bereich
34,360 MHz bis 39,840 MHz**

Kanal	Frequenz oder Frequenzpaar MHz	Kanal	Frequenz oder Frequenzpaar MHz
810	34,360/38,460	841	39,260
802	34,380/38,480	842	39,280
803	34,400/38,500	843	39,300
804	34,420/38,520	844	35,220/39,320
805	34,440/38,540	845	35,240/39,340
806	34,460/38,560	846	35,260/39,360
807	34,480/38,580	847	35,280/39,380
808	34,500/38,600	848	35,300/39,400
809	34,520/38,620	849	35,320/39,420
		850	35,340/39,440
821	38,860	851	35,360/39,460
822	38,880	852	35,380/39,480
823	38,900	853	35,400/39,500
824	38,920	854	35,420/39,520
825	38,940	855	35,440/39,540
826	38,960	856	35,460/39,560
827	38,980	857	35,480/39,580
828	39,000	858	35,500/39,600
		859	35,520/39,620
		860	35,540/39,640
831	34,960	861	35,560/39,660
832	34,980/39,080	862	35,580/39,680
833	39,100	863	35,600/39,700
834	39,120	864	35,620/39,720
835	39,140	865	35,640/39,740
836	39,160	866	35,660/39,760
837	39,180	867	35,680/39,780
838	39,200	868	35,700/39,800
839	39,220	869	35,720/39,820
840	39,240	870	35,740/39,840
		871	35,760
		872	35,780
		873	35,800

Sachstand: 11.01.2000